

IO954N

Apollo Mains Switching IO Unit (SA4700-103)

General

IO954N is the new mains switching input/output unit which contains one or more normally open contacts connected to a single pair of cables. It also provides a voltage free change over relay output capable of switching mains.

Mechanical Construction

The IO954N is available in the new faceplate style enclosure. It is designed to be surface mounted to the wall and consists of 3 parts:

- a back box with knock-outs for cable entry
- a PCB assembly
- a protective front cover

Ease of Installation

Improved design for ease of wiring meaning faster installation – unit can be fitted to back-box before wiring is connected. Colour coded terminal blocks for easier identification (green for loop wiring, yellow for mains wiring, grey for inputs and low voltage relays).



Details

- Improved design for ease of wiring meaning faster installation
- Loop powered
- Contains one or more NO contacts connected on a single pair of cables
- Local LEDs signalling I/O and fault conditions
- Isolators within each device

IO954N

Apollo Mains Switching IO Unit (SA4700-103)

Especificaciones técnicas

Eléctrico

Operating voltage	17 to 35 VDC
-------------------	--------------

Físico

Dimensiones físicas	150 x 90 x 60 mm
---------------------	------------------

Net weight	301 g
------------	-------

Medioambiental

Operating temperature	-40 to +70°C
-----------------------	--------------

Relative humidity	0 to 95% noncondensing
-------------------	------------------------

Environment	Interior
-------------	----------

Regulador

Certificación	CPR, EN54-17, EN54-18
---------------	-----------------------

Electrical

Protocol voltage	5-13V peak to peak
------------------	--------------------

Current consumption

Power-up surge	1.1 mA
----------------	--------

Quiescent	0.7 mA
-----------	--------

LEDs disabled (max.)	0.7 mA
----------------------	--------

Alarm (LEDs On) (max.)	5.2 mA
------------------------	--------



Como empresa innovadora, Carrier Fire & Security se reserva el derecho de modificar las especificaciones de los productos sin previo aviso. Para conocer las últimas especificaciones de los productos, visite la Web de es.firesecurityproducts.com o póngase en contacto con su comercial.

Last updated on 4 May 2023 - 17:07